


Avaya 9508 Telephone Instructions

New telephone installation Help Desk Number: 4357

Function	Steps	Function	Steps
To Answer a Call	Pick up the Handset – or – Press [SPEAKER]	To Transfer a Call To Another Extension	DO NOT PRESS HOLD • Press [TRANSFER]
To Make a Call Outside the Office	 Pick up the Handset – or – Press [SPEAKER] Dial the access code "9" Dial the telephone number 		Enter the "Transfer to:" extension Press [TRANSFER] or Complete immediately. You can also wait for the called party to answer and announce the call before pressing [TRANSFER] or
To Call a Telephone Extension In the Office	Pick up the Handset – or – Press [SPEAKER] Dial the extension number		Complete Peture the collecte year
Muting a Call	 Press [Mute] during a call so that the other person on call cannot hear you. Press [Mute] again to unmute the call. Note: When you mute the call, the Mute button light is on and the top line displays the Mute icon 		Return the caller to you If the called party does not answer or does not want the transfer, press [DROP]. To return to the held call, press the call appearance key where the call is blinking.
Leave Message For Internal Callers Leave a Message without Ringing an Extension	 Pick up Handset Enter # plus the mailbox number, (Ex: #2111) At the tone, leave your message 		
To Place a Call on Hold To return to the Caller	 Press the button labeled [HOLD] Press the <u>Extension</u> or <u>Line</u> key with the flashing indicator Note: The line flashing very quickly or without a _ under the handset is YOUR held call. If the light(s) blink slowly or if there is a _ under the handset, it was placed on hold by someone else. 	To Make a 3-Way Conference Call	 Make or answer the first call Press [CONFERENCE] This places the first call on hold automatically Make the second call Press [CONFERENCE] again to begin the conference If the called party does not answer or does not want to join the conference, press [DROP]. To return to the held
To Hang-up	Press [DROP] OR Press [SPEAKER] if the call is "handsfree" OR Return the handset to the cradle		call, press the call appearance key where the first call is blinking.
DND (Do Not Disturb)	Press [DND] to temporarily disable ringing and forward all calls directly to voicemail Press [DND] again to cancel	Transfer to Voicemail Transfer a Caller to a Mailbox	Press [MESSAGE] Envelope Button (Do not place caller on hold) Enter the extension number Press the Select soft key to transfer the call To exit the Transfer Menu on Display, Press Cancel OR
			Transfer the caller to # plus the Mailbox number



Avaya 9508 Telephone Instructions

New telephone installation Help Desk Number: 4357

Function	Steps	Function	Steps
Contacts (Personal Speed Dial) Up to 100 Entries	To Dial from Contacts 1. Press Directory key. (Directory menu is displayed) 2. Use the left and right arrows keys to select which type of directory entries you want displayed: ALL (System Directory, Personal & External) PERSONAL (Individual Speed Dial) EXTERNAL (Shared Speed Dial) 3. Use the list or start dialing the name to find matching entries 4. Press Call when your selected contact is highlighted To Add an Entry – Personal 1. Press Directory key. (Directory menu is displayed)	€ History	To View the Call Log 1. Press the HISTORY button. The display will change to show your call log records. The caller's name is shown if known, otherwise the number. 2. Use the ↓ up and down ▼ arrow keys to select which call log records you want to view. (All, Missed, Incoming & Outgoing) If you have any new missed call records, the ↓ HISTORY button lamp is illuminated. 3. Use the ↓ up and down ▼ arrow keys to scroll through the records. 4. Press Details to view additional information
	 Press the New soft key. Enter Name Example: To spell the name "Don" on your Dial Pad: Press 3 once, for the Letter D. Press 6 three times, for the Letter O Press 6 twice, for the Letter N Enter Number Press the Save soft key. (Your new Entry is now saved) The new entry will show in ALL or PERSONAL display 	Change Ringer	 To call external number: Lift handset, dial 9, then press Call Press the A HOME button Use the A up and down ▼ arrow keys to highlight: Screen & Sound Options, Press Select. Personalized Ringing, Press OK Use A up and down ▼ arrows to scroll through available ring
	To Delete an Entry 1. Press Directory key (arrow right to Personal Display) 2. Find and highlight your entry to be deleted 2. Press the More soft key 3. Press the Delete 4. Press the Delete soft key again to confirm the action. Press the Cancel soft key to exit without making changes		tones. 6. Press Play soft key to listen to the displayed ring tone. 7. Press Other to hear a different version of ring tone. 8. Press Save soft key 9. Press PHONE to exit the menus Press Cancel soft key if you wish to make no changes
(Shared Speed Dial) **Programmed by System Administrator	*Note: You can only delete/modify your Personal entries To Dial from Shared External Directory 1. Press Directory key (arrow right to External Display) 3. Use the ↓ up and down ▼ arrow keys to scroll through the list or start dialing the name to find matching entries 4. Press Call when your selected contact is highlighted	Change Contrast	 Press the A HOME button. Use the A up and down ▼ arrow keys to highlight Screen & Sounds. Press Select. Use the up and down arrow keys to highlight Contrast. Press OK. Use the A up and down ▼ arrow keys to change display Press Save soft key. Press PHONE to exit the menus

Avaya 9508 Telephone Instructions

New telephone installation Help Desk Number: 4357

9508 Telephone

